

500W

Portable Power Station

AC outlets	Yes, 2
USB-A outlets	Yes, 3
USB-C outlets	Yes, 1
Micro USB outlets	No
Mini USB outlets	No
Lightning outlets	No
No. devices connected at once	9
Input interface	DC, USB Type-C, Andreson
On/Off switch	Yes (AC, DC & USB)
Built-in display	Yes, LCD
LED indicators	Yes, port use status
Charger compatibility	AC, DC, USB Type-A, USB Type-C
Charging source	AC, DC, USB Type-C, solar
Simultaneously power and charge	Yes (except for the AC output)
PowerIQ	No
Fast charging	Yes, QC 3.0 & PD 3.0
Wireless charging	No
Battery technology	LiFePO4
No. of battery cells	48
No. of charging cycles	2000 cycles to 80% capacity
Efficiency	85 - 95%
Battery voltage	19.2V
Battery capacity	32Ah / 192000mAh / 614Wh
Battery charge time via AC port (96W)	~ 8 hours
Battery charge time via DC port (48W)	~ 15 hours
Battery charge time via USB port (60W)	~ 12 hours
Input voltage	11 - 26V
Input current	4A
Adjustable output voltage	No
AC output voltage	220-240V
DC output voltage	12V
USB-A port output voltage	5V
USB-A QC3.0 output voltage	5-12V
USB-C PD output voltage	5-20V
Total output power	600W



Part no. PX-500WPS

In case of a power failure, or when you are out traveling, a fully charged ProXtend PX500 Power Station can power and charge devices simultaneously.





500W

Portable Power Station

USB power delivery	Yes, up to 60W
Operating temperature	0° ~ 45° C
Storage temperature	-5° ~ 60° C
Relative operating humidity	0% ~ 65%
Relative storage humidity	10% ~ 75%
International Protection code	No
Protection features	BMS protection, V0 fireproof housing
Built-in mirror	No
Built-in compass	No
Housing material	ABS, polycarbonate
Product shape	Rectangle
Product color	Black, orange
Certification	CE (EMC & LVD), RoHS, UN38.3, MSDS
Dimensions	W322mm x D202mm x H227mm
Weight	8000g
Battery weight	4128g
Included cables	1x car charging cable
Adapters included	Yes, 1
Package type	Kraft box
User manual included	Yes
Country of origin	China



Part no. PX-500WPS

In case of a power failure, or when you are out traveling, a fully charged ProXtend PX500 Power Station can power and charge devices simultaneously.

